

## **ZERO-OHM RESISTORS**

## Series : MZOR

beries		<u>IMZUR</u>						
Featur	res:							
Insulated body allows to be passed over tracks without short circuiting.								
Can be tape mounted for auto insertion machines.								
<ul> <li>Remove the need of double sided PCB boards in some cases.</li> </ul>								
Dimen	isions :							
-		— H			L		→   ↓ 	Ød
							↑ Ø D	
Physic	al Data:							
ТҮРЕ	WATT.	DIMENSIONS (mm)						
		L	D	d ± 0.05	н			
MZOR	0.25W	6.5± 0.5	2.3 ±0.2	0.6	25 min			
		BLACK colour.		resistan	ce & 101e1	rance are marked	i on the resistor b	ody using <b>ONE</b> coloured
		ng Informatio						
Part Nu	mber : MZ	20R, 0.25W, 0 (	OHMS					• •
Packin	ng Inforr			1				
TYPE		Pcs Per Poly Bag/ Blue box		Pcs Per Br		rown Box	Pcs Per Real	
MZOR		1,000 5,		5,00	00	5000		
Perfor	mance L	Data :						
	DESCRIPTION					SPEC	CIFICATION	
Current carring capacity					amps	5 max.		
Isolation voltage					volts	500 dc or ac peak		
Insulation resistance ohms					ohms	> 1 G		
Voltage proof volts					volts	350 dc or ac peak		
	I - ^ .							

All information is subject to MFR's own data & is considered accutate at the time of going to print.